

SES AYARLAMA

SES KAPATMA

TUS KILIDI

MODLAR


VOL BASILI TUT 

VOL BAS 

PWR BAS 

Dx BAS
 ■ DN (AUTO DM)
 DN (CF4M) (WIDE DM)
 VW (HQ DIG) (WIDE DM)
 TN (TONE ENCD)
 TSQ (TONE SQLC)
 FM (ANALOG)
 ■ FM (AUTO ANLG)

TEK ELLE SES AYARLAMA

DISP BASILI TUT  ▶ 2 TX / RX
 ▶ 3 AUDIO ▶ DISP
 ▶ 4 VOL MODE
 ▶ AUTO BACK

SQUELCH

F  ▶ MONI T-CALL MONI MODDA  ▶ AYARLA  ▶ PTT KAYIT


TX GONDERME GUCU

F  1  ▶ L1▶L2▶L3▶HI  ▶ PTT KAYIT

A / B BANDLARI ARASI GECIS

A/B GONDERILECEK BAND SECIMI  ▶ A/B  ▶ A/B BASILI TUT ▶ MONO

VFO / BANK TARAMA

F  2 TARAMA BASLAT  ▶ PTT CIK

EKRANDA PIL VOLTAJINI GORME

A/B BASILI TUT ▶ MONO  F PIL VOLTAJINI GORME  A/B

CESITLI

TX GONDERME GUCU
 L1 : 0.1 W - L2 : 1.0 W - L3 : 2.5 W - HI : 5.0 W

METIN DUZENLEME
 A/B CLR : SONA - INSERT : KRKTR V/M
 DELETE : KRKTR - CLRALL : TUM V/M

METIN GRISI
 ENT GIR  F GERI  SEC  PTT KAYIT

BAND KAPSAMI
 V/M MR ▶ VFO  AYARLA  BAND BASILI TUT

DOGRDN KAYITLI KANAL CAGIR
 #  ENT KANAL NUMARASI

VFO DAN KANAL KAYDETME

VOL MR ▶ VFO  AYARLA  F BASILI TUT  SECIM  F BASILI TUT

ROLE SHIFT / SIMPLEX AYARLAMA

DISP BASILI TUT  8 CONFIG  ENT  15 RPT SHIFT  ENT


CTCSS TONE ACMA / KAPAMA

DISP BASILI TUT  4 SIGNALING  ENT  11 SQL TYPE  ENT

CTCSS TONE FREKANSI AYARI

DISP BASILI TUT  4 SIGNALING  ENT  12 SQL SQL  ENT

HAFIZA ISMI / HAFIZA UZERINE YAZMA KORUMASI

DISP BASILI TUT  3 MEMORY  ENT  4 MEM PROTECT 3 MEM NAME  ENT





HAFIZA BANK






BAND MR ▶ BANK  F  BAND  BANK SEC  BAND KAYIT





VFO / BANDLAR / AM / FM

V/M MR ▶ VFO  TUNE  BAND BAND YUKARI  F  BAND BAND ASAGI

APRS ACMA






DISP BASILI TUT  9 APRS  A/B B BANDINI SEC  144.800 MHz  DISP BAS






 20 GPS PWR  ENT GPS ON  24 MY POS  ENT SEL GPS-P1..P10  DISP BAS






 14, 15, 16, 27  ENT  ENT  DISP BAS

- ▶ 14 BEACON INTERVAL : MIN 5 MINUTE
- ▶ 15 BECN STAT TXT : ON / TX RATE SEL / TXT SEL
- ▶ 16 BECN TX : AUTO
- ▶ 27 SMART BEACNING : TYPE 1

APRS MESAJLARI

 F  0 APRS MSG LIST  0  CAGRI ISRT / MSJ TKRR KUL.MA  ENT





 GM  GIR CALL / SSID  GIR MESAJ /  A/B SABIT METIN SECME  V/M BCON TX

 ENT GOND. IGN BAS. TUT  V/M MSJ SIL  EL ILE BEACNING  F  9

GPS KONUM / BILGI

DISP BASILI TUT  1 DISPLAY  ENT  1 GPS PWR  ENT BAS

HAVA DURUMU BANDI (ONCEDEN AYARLI BANDLAR ICIN BAND TUSUNA BAS)

A/B A-BAND  F  3 P. RCVR  BAND WX SEC  3 CIK

BEACON KISAYOLU

 F APRS MSJ LİSTESİ  0 S.LİST-APRS  BAND EL İLE / OTO  AUTO  SMART